

AN664

Converting from 93xx46 Devices to 93xx46A/B Devices

DESCRIPTION

This application note details the process of converting from 93C06, 93C46 and 93LC46 type devices to 93C46B, 93LC46A, and 93LC46B devices. The new 93xx46A/B devices include improved data polling operation and are available in the small 8 pin TSSOP package. The new devices also offer fixed device organization. For example the "A" suffix on the 93LC46A part number indicates that the device is organized as x8 only. The "B" suffix indicates that the 93LC46B is organized as x16 only.

The new devices also incorporate power protection circuitry that adds extra data protection when powering down the device. The 93C46B is designed to function as a 4.5V - 5.5V part. An internal voltage detect circuit prevents write operations below nominally 3.8 volts. The 93LC46A and 93LC46B devices have an internal voltage detect that inhibits writes below 2.2V nominally.

In the table below the operation parameters of the old and new devices are outlined.

Part Number	Organization	Operating Range
93C46	x16 only	4.5V - 5.5V
93LC46	x8 or x16	2.0V - 6.0V
93LC46B	x16 only	2.0V - 6.0V
93AA46	x8 or x16	1.8V - 6.0V
93C46B New	x16 only	4.5V - 5.5V
93LC46A New	x8 only	2.5V - 6.0V
93LC46B New	x16 only	2.5V - 6.0V

The following product conversion decision tree will assist in converting to the new 93xx46A/B products. In order to properly convert to new products two items need to be known about the existing application, the operating voltage of the system and whether the memory is organized as x8 or x16. Once that information is know then the decision tree will assist in determining what the new product should be. The product selection is also available in tabular form on page 2.

PRODUCT CONVERSION DECISION TREE



Part number currently being used	Voltage Range	Organization	New part number to be used
93C06	All	All	NEW 93C46B
93C46	All	All	NEW 93C46B
93LC46	2.5V - 6.0V	x8	NEW 93LC46A
93LC46	2.5V - 6.0V	x16	NEW 93LC46B
93LC46	2.0V - 2.5V	All	93AA46
93LC46B	2.5V - 6.0V	All	NEW 93LC46B
93LC46B	2.0V - 6.0V	All	93AA46B

TABLE 1 PRODUCT CONVERSION TABLE

VOLTAGE OPERATION GRAPHS

The following two graphs show the operating voltages of the current 93xx46 devices and the **NEW** 93xx46A/B devices. From the graphs it can be seen that there is a voltage range covered by the existing devices that is not covered by the new devices. The continued production of the 93AA46 device ensures that anyone currently operating in the voltage range not covered by the new 93xx46A/B devices will have a conversion solution.



NOTES:

WORLDWIDE SALES & SERVICE

AMERICAS

Corporate Office

Microchip Technology Inc. 2355 West Chandler Blvd. Chandler, AZ 85224-6199 Tel: 602-786-7200 Fax: 602-786-7277 Technical Support: 602 786-7627 Web: http://www.microchip.com

Atlanta

Microchip Technology Inc. 500 Sugar Mill Road, Suite 200B Atlanta, GA 30350 Tel: 770-640-0034 Fax: 770-640-0307

Boston

Microchip Technology Inc. 5 Mount Royal Avenue Marlborough, MA 01752 Tel: 508-480-9990 Fax: 508-480-8575

Chicago

Microchip Technology Inc. 333 Pierce Road, Suite 180 Itasca, IL 60143 Tel: 708-285-0071 Fax: 708-285-0075

Dallas

Microchip Technology Inc. 14651 Dallas Parkway, Suite 816 Dallas, TX 75240-8809 Tel: 972-991-7177 Fax: 972-991-8588

Dayton

Microchip Technology Inc. Two Prestige Place, Suite 150 Miamisburg, OH 45342 Tel: 937-291-1654 Fax: 937-291-9175

Los Angeles

Microchip Technology Inc. 18201 Von Karman, Suite 1090 Irvine, CA 92612 Tel: 714-263-1888 Fax: 714-263-1338

New York

Microchip Technology Inc. 150 Motor Parkway, Suite 416 Hauppauge, NY 11788 Tel: 516-273-5305 Fax: 516-273-5335

San Jose

Microchip Technology Inc. 2107 North First Street, Suite 590 San Jose, CA 95131 Tel: 408-436-7950 Fax: 408-436-7955

Toronto

Microchip Technology Inc. 5925 Airport Road. Suite 200 Mississauga, Ontario L4V 1W1, Canada Tel: 905-405-6279 Fax: 905-405-6253

ASIA/PACIFIC

Hong Kong

Microchip Asia Pacific RM 3801B, Tower Two Metroplaza 223 Hing Fong Road Kwai Fong, N.T., Hong Kong Tel: 852-2-401-1200 Fax: 852-2-401-3431

India

Microchip Technology India No. 6, Legacy, Convent Road Bangalore 560 025, India Tel: 91-80-299-4036 Fax: 91-80-559-9840

Korea

Microchip Technology Korea 168-1, Youngbo Bldg. 3 Floor Samsung-Dong, Kangnam-Ku Seoul, Korea

Tel: 82-2-554-7200 Fax: 82-2-558-5934 Shanghai

Microchip Technology RM 406 Shanghai Golden Bridge Bldg. 2077 Yan'an Road West, Hongiao District Shanghai, PRC 200335 Tel: 86-21-6275-5700 Fax: 86 21-6275-5060

Singapore

Microchip Technology Taiwan Singapore Branch 200 Middle Road #10-03 Prime Centre Singapore 188980 Tel: 65-334-8870 Fax: 65-334-8850

Taiwan, R.O.C

Microchip Technology Taiwan 10F-1C 207 Tung Hua North Road Taipei, Taiwan, ROC Tel: 886 2-717-7175 Fax: 886-2-545-0139

EUROPE

United Kingdom Arizona Microchip Technology Ltd. Unit 6, The Courtyard Meadow Bank, Furlong Road Bourne End, Buckinghamshire SL8 5AJ Tel: 44-1628-851077 Fax: 44-1628-850259

France

Arizona Microchip Technology SARL Zone Industrielle de la Bonde 2 Rue du Buisson aux Fraises 91300 Massy, France Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79

Germany

Arizona Microchip Technology GmbH Gustav-Heinemann-Ring 125 D-81739 Müchen, Germany Tel: 49-89-627-144 0 Fax: 49-89-627-144-44

Italy

Arizona Microchip Technology SRL Centro Direzionale Colleone Palazzo Taurus 1 V. Le Colleoni 1 20041 Agrate Brianza Milan Italy Tel: 39-39-6899939 Fax: 39-39-6899883

JAPAN

Microchip Technology Intl. Inc. Benex S-1 6F 3-18-20. Shin Yokohama Kohoku-Ku, Yokohama Kanagawa 222 Japan Tel: 81-4-5471- 6166 Fax: 81-4-5471-6122

1/14/97



Printed on recycled paper.

Information contained in this publication regarding device applications and the like is intended for suggestion only and may be superseded by updates. No representation or warranty is given and no liability is assumed by Microchip Technology Incorporated with respect to the accuracy or use of such information, or infringement of patents or other intellectual property rights arising from such use or otherwise. Use of Microchip's products as critical components in life support systems is not authorized except with express written approval by Microchip. No licenses are conveyed, implicitly or otherwise, under any intellectual property rights. The Microchip logo and name are registered trademarks of Microchip Technology Inc. in the U.S.A. and other countries. All rights reserved. All other trademarks mentioned herein are the property of their respective companies.

